

PH: 1300 743 529
www.hightechgenerators.com.au

\$1,469

1800 Running Watts*
2400 Starting Watts**



Model	P2400
Part Number	030802
NumberOf Outlets	3
Engine	Briggs& Stratton [®] OHV
Displacement	79cc
Amperage	15A
Voltage	230V AC
Auto Idle	Yes
Auto Voltage Regulation	Inverter

Fuel Tank Capacity(L)	3.7
Muffler	Yes - Spark ArrestorType
Weight(Kg)	22.8 kg
Low Oil Protection System	Yes
RCD	No
Dimensions L x W x H(mm)	509 X 311 X 441
Warranty Consumer	3 Years Limited Warranty
Commercial	1 Year Limited

COGuard - Shuts down your generator when harmful levels of carbon monoxide are detected

QPT™ Quiet Power Technology - Automatically adjusts the engine speed further reducing noise and fuel consumption

Easy Portability with 2-person H-Beam Carry Handle

The PowerSmart Series Inverter Generators deliver 'pure sine waves' at 2400 watts peak and 1800 watts continuous making it ideal for sensitive electronic equipment

Pull Start

- Parallel Kit Socket - Utilizing the B&S Parallel Kit (p/n 6330) you can join a 2400 with another 2400

Overload, circuit breaker and low oil protection indicators

Up to 8 hours run time @ 25% load

* Per CSA C22.2 No. 100-14 and ANSI/PGMA G300-2018

** Starting Watts is the maximum current that can momentarily be supplied when starting a motor, multiplied by the generator's rated voltage.

See www.briggsandstratton.com for warranty details.

Briggs & Stratton has a policy of continuous product improvement and reserves the right to modify its specifications at any time and without prior notice. Product may vary from images shown.