

EF2800i

2.8 kVA Inverter Generator

Smooth power for your building site!

Introducing the portable EF2800i Inverter Generator, delivering maximum output with minimum effort. This generator is powerful and portable, it will run it all and more.

What can it run?

- Fridge
- Desktop Computer
- Toaster
- Lights
- Hair Dryer
- Coffee Maker
- Belt Sander
- High Pressure Washer
- Air Compressor
- Kettle
- Television
- Portable Heater
- Laptop Computer
- Airconditioner
- Electric Hand Drill
- Chainsaw
- Bench Grinder
- Circular Saw

Not only is this generator perfect for the worksite, but is great for backing up your home when the power goes out.



EF2800i

SPECIFICATION

| | EF2800i |
|------------------------------|---------------|
| Maximum Output | 2.8 KVA |
| Rated Output | 2.5 KVA |
| Operating Hours (1/4 Load) | 17 hr |
| Fuel Tank Capacity | 11.2 L |
| Size (LxWxH) | 487x395x425mm |
| Dry Weight | 29 kg |
| Noise Level (1/4 Load / 7m) | 60dBA |
| Noise Level (Full Load / 7m) | 67dBA |
| Starting System | Recoil |
| Independent Fuel Tap | Yes |
| Fuel Gauge Monitor | Yes |

FEATURES AT A GLANCE

- **The Lightest Generators** in their class weighing only 29 kg each
- **USFS - Approved Spark Arrestor** eliminate errant spark.
- **OHV Engine With Cast Iron Cylinder Liner** for longer life, powerful performance and excellent heat dissipation.
- **Smart Throttle™** varies engine speed based on load to improve fuel economy and reduce noise.
- **Inverter System with PWM** (Pulse Width Modulation) to safely run products with built-in microcomputers or microcomputer equipment / tools.
- **Petrol Petcock** helps prevent carburettor contamination during storage.
- **Oil Warning System** prevents engine damage.
- **Fuel Gauge** displays fuel levels without having to open the fuel cap.
- **Auto-Decompression System** reduces compression for effortless starting.
- **Electrical Overload Breaker** prevents generator damage in case of overload.
- **Controls Located On One Panel** for easy access.
- **Rubber Isolation Feet** for smooth operation and noise absorption.
- **Easily Detachable Side Panels** for easier serviceability.
- **Multi-Polar Alternator** for the generation of high quality, high frequency 3-phase AC current. This means a much lighter and a more compact unit when compared to conventional 2-pole rotor type alternators.

*All information and specs are subject to change without notice. Product running capabilities are dependant on the particular products wattage usage, not all appliances can run at the same time.

Yamaha data, April 2016.