



**\$2,049**

## P3400 PowerSmart Series™ Inverter Generator

The P3400 PowerSmart Series™ Inverter Generator by Briggs & Stratton takes portable power generation to the next level. Inverter technology makes it safer for sensitive electronics and computer controlled technology supplies smooth, steady power – and adjusts engine speed accordingly to suit your power needs and save fuel. Twin cushioned carrying handles or a retractable handle and wheels make it easy to move. Plus the on-board LCD StatStation® display keeps you informed about power use, run time and maintenance reminders. Now that's smart power.

**171**

Displacement (cc)

**8**

Run Time @ 1/4 Load  
(hrs)

**2800**

Running Watts

**3400**

Starting Watts

Model Number	030808
Running Watts	2800
Starting Watts*	3400
Outlet	2 x 230V 15A Outlets, 1 x 12V 5A DC Charging Outlet, 2 x USB Ports
Muffler	Standard
Voltage	230
Start Type	Recoil
Alternator	Permanent Magnet
Displacement (cc)	171
Run Time @ 1/4 Load (hrs)	8
Fuel Tank Capacity (L)	5.7
Fuel Gauge	Yes
Low Oil Shutdown	Yes
Hour Meter	Part of StatStation™
Transport Handle	Telescoping Handle and H beam carry Handle
Wheel Diameter (in)	6
Weight (kg)	38.6
Length with Wheels (mm)	660
Width with Wheels (mm)	352
Height with Wheels (mm)	517
Starter Type	Recoil