

\$3,499

3700 Running Watts*
4500 Starting Watts**



Model	P4500
Part Number	030807
Number Of Outlets	3
Engine	Briggs & Stratton [®] OHV
Displacement	224cc
Amperage	15A
Voltage	230V AC
Auto Idle	Yes
Auto Voltage Regulation	Inverter

Fuel Tank Capacity (L)	13.2
Muffler	Yes - Spark Arrestor Type
Weight (Kg)	47
Low Oil Protection System	Yes
RCD	No
Dimensions L x W x H (cm)	62.2 x 44.7 x 51.6
Warranty Consumer	3 Years Limited Warranty ¹
Warranty Commercial	1 Year Limited Warranty ¹

- COGuard - Shuts down your generator when harmful levels of carbon monoxide are detected
- QPT™ Quiet Power Technology - Automatically adjusts the engine speed further reducing noise and fuel consumption
- Easy Portability with telescopic handle along with side hold handles and integrated wheels

- The PowerSmart Series Inverter Generators deliver 'pure sine waves' at 4500 watts peak and 3700 watts continuous which makes it ideal for sensitive electronic equipment
- Electric Push Button Start and Remote
- Statstation™ Digital Display - Displays power usage, total unit lifetime hours, and maintenance reminders.
- Up to 16 hours run time @ 25% load

* Per CSA C22.2 No. 100-14 and ANSI/PGMA G300-2018

** Starting Watts is the maximum current that can momentarily be supplied when starting a motor, multiplied by the generator's rated voltage.

¹ See www.briggsandstratton.com for warranty details.

Briggs & Stratton has a policy of continuous product improvement and reserves the right to modify its specifications at any time and without prior notice. Product may vary from images shown.